

FEATURES

1. Water-proof and dust-proof for all-weather races; (Note: please uninstall the cooling fan before using this ESC in waters. Clean and dry it soon after the use for avoiding the connectors getting rusty.)
 2. Specially designed for RC car with excellent start-up acceleration and linearity features.
 3. Compatible with sensorless brushless motor.
 4. The strong resistant current capability, excellent heat dissipation
 5. Multiple protection features: Low voltage cut-off protection for lithium or nickel battery/Over-heat protection/Throttle signal loss protection/Motor blocked protection/
 6. Easily programmed and compatible with pocket-sized program card
- CONNECTIONS
Connect to Battery Connect to motor
Connect to Receiver Switch

Specifications:

Model 120A

Burst Current Cont. Current 120A

Sensorless Brushless Motor Sensorless Brushless Motor

6.5mm Banana connector

For 4S Lipo or 12 cells NiMH: For 4S Lipo or 12 cells NiMH

1. on-road: 40XX-size or smaller motor with the KV < 3000
1. on-road: 42XX-size or smaller motor with the KV < 3000
Motor Type with the KV < 2500

2. Off-road/Buggy/Monster: 40XX-size or smaller motor with the KV < 2500

3. Off-road/Buggy/Monster: 42XX-size or smaller motor

